

# SM435C Real-Time Spectrum Analyzer & Monitoring Receiver

100 kHz to 43.5 GHz  
with 160 MHz BW I/Q Streaming over 10 GbE

14 July 2022



The SM435C is a high-performance spectrum analyzer and monitoring receiver with a 10 Gigabit Ethernet SFP+ port, which enables the SM435C to communicate with a PC over long distances using fiber optic cable. Tuning from 100 kHz to 43.5GHz, the analyzer has 160 MHz of instantaneous bandwidth (IBW), 110 dB of dynamic range, 1THz/sec sweep speed at 30kHz RBW (using Nuttall windowing), and ultra-low phase noise to rival even the most expensive spectrum analyzers on the market.

Signal processing is distributed between a powerful Intel FPGA and an external PC having an Intel Core i7 processor. The Signal Hound SM435C can be readily interfaced, using its local API, to an automated monitoring system or to automated test equipment. The SM435C API provides customers the access needed to insert their own DSP algorithms into a calibrated stream of I/Q data.

## PRELIMINARY SPECIFICATIONS

### FREQUENCY

- **Range:** 100 kHz to 43.5 GHz
- **RF Input Impedance:** 50Ω (2.4mm connector)
- **RF Input VSWR (Ref Lvl = 0 dBm):** 1.45 from 50 MHz to 10 GHz  
1.7 from 10 to 20 GHz  
2.0 from 20 to 43.5 GHz
- **Calibrated Streaming I/Q:** 5 kHz to 40 MHz of selectable I/Q streaming bandwidth
- **Up to 2 seconds of Calibrated I/Q Capture** at 160 MHz bandwidth
- **Resolution Bandwidths (RBW):** 0.1 Hz ( $\leq 200$ kHz span) to 3MHz (any span) using 40 MHz IBW; 30 kHz to 10 MHz using 160 MHz IBW
- **Timebase Accuracy:** GPS disciplined OCXO remains within
  - $\pm 5 \times 10^{-10}$  when locked to GPS
  - holdover of  $\pm 5 \times 10^{-9}$  /day for aging ( $\pm 2 \times 10^{-8}$  first day typ)
  - holdover of  $\pm 1 \times 10^{-8}$  for temperature over -40°C to 65°C (typ)

### SYSTEM NOISE FIGURE (Typical)

- 12dB over 700 MHz to 2.5 GHz;
- 15dB from 2.5 GHz to 24 GHz;
- 18dB + 0.5dB/GHz from 24 GHz to 40 GHz;
- 26dB + 2.0dB/GHz from 40 GHz to 43.5 GHz

### IP<sub>2</sub> +75dBm from 100 kHz to 20 GHz

- +50dBm from 20 GHz to 24 GHz
- +70dBm from 24 GHz to 43.5 GHz

### IP<sub>3</sub> +28dBm from 100 kHz to 4 GHz;

- +23dBm from 4 GHz to 6 GHz;
- +20dBm from 6 GHz to 43.5 GHz



# SM435C Real-Time Spectrum Analyzer & Monitoring Receiver

## SWEEP SPEED

Speed	RBW
1THz/sec	1MHz
1THz/sec	100kHz
1THz/sec	30kHz
160GHz/sec	10kHz
18GHz/sec	1kHz

## AMPLITUDE ACCURACY (+10 dBm TO DISPLAYED AVERAGE NOISE LEVEL (DANL))

100 kHz to 6 GHz	Above 6 GHz	RBW filter shape
±2.0 dB	±3.0 dB	Flat-Top windowing
+2.0 dB/-2.6 dB	+3.0/-3.6 dB	Nuttall windowing

## DISPLAYED AVERAGE NOISE LEVEL (DANL)

Input Frequency Range	dBm/Hz
100 kHz to 160 MHz	-156 dBm
160 MHz to 2.2 GHz	-159 dBm
2.2 GHz to 24 GHz	-155 dBm
24 GHz to 36 GHz	start -153 dBm + 0.5dB/GHz
36 GHz to 43.5 GHz	start -147 dBm + 1.1dB/GHz

## RESIDUAL RESPONSES: REF LEVEL ≤ -20 dBm, 0 dB ATTENUATION, 50-ohm load on RF input

Input Frequency Range	Residual Level
100 kHz to 6 GHz	-110 dBm
6 GHz to 15 GHz	-100 dBm
15 GHz to 44 GHz	-90 dBm

**LO LEAKAGE @ RF INPUT:** -80 dBm from 100 kHz to 6 GHz; -50 dBm from 6 GHz to 24 GHz; -75 dBm from 24 to 43.5 GHz

**SUB-OCTAVE PRESELECTOR FILTERS** 20 MHz-43.5 GHz

**SPURIOUS MIXER RESPONSES (any ref level (RL) from +10 dBm TO -20 dBm, in 5 dB increments, input 10 dB less than RL, RBW ≤30kHz, IBW ≤40MHz):**

Input Freq. Range	Image Reject Off	Image Reject On
100 kHz to 6 GHz	-55 dBc	-75 dBc (typ)
6 GHz to 24 GHz	-45 dBc	-75 dBc (typ)
24 GHz to 43.5 GHz	-45 dBc	-65 dBc (typ)

## SYNCHRONIZATION

GPS data in each packet with ± 40ns timestamping

**Note:** Signal ID/image reject can be activated and deactivated, by toggling the F3 key on keyboard, to allow low level mixer spurs to be differentiated from RF Input signals. \*Above 40 GHz, spurs above -50 dBc typically > 5 GHz from signal

All specifications are preliminary and subject to change without notice.

## SYSTEM REQUIREMENTS

External PC with Microsoft® Windows® 10, Ubuntu® 18.04, or CentOS® 7. A 10GbE SFP+ port (NIC or Thunderbolt 3 with recommended SFP+ to Thunderbolt 3 adapter) is also required to operate the SM200C. 200MS/s I/Q streaming requires an SSD for rapid mass data storage during IQ recording and a minimum of an Intel® 8th generation or newer i7 processor (for laptops), or 6th generation or newer i7 processor (for desktops). Refer to SM200C 10GbE Network Configuration Guide for further information.

## SSB PHASE NOISE AT 1 GHz CENTER FREQUENCY

Offset Frequency	dBc/Hz
10 Hz	-76
100 Hz	-108
1 kHz	-125
10 kHz	-136
100 kHz	-138
1 MHz	-138

## SSB PHASE NOISE AT 20 GHz CENTER FREQUENCY

Offset Frequency	dBc/Hz
1 MHz	-112
10 MHz	-131

## FPGA

Intel 10AX027 has 1660 multipliers, provides selectable decimation, 160 MHz of instantaneous bandwidth from FFT processing w/ resources to spare for future growth.

## OPERATING TEMPERATURE (AMBIENT)

- Standard (passive cooling) 32°F to 122°F (0°C to +50°C)
- Option-1 (active cooling & extended temperature) -40°F to 149°F (-40°C to +65°C)

## SIZE AND WEIGHT

- 10.45" x 7.20" x 2.15" (265mm x 183mm x 55mm) passive cooling 8.15 lbs. (3.70 kg) passive cooling **plus** 1.45 lbs. (0.65 kg) for AC power module and AC power cord
- 10.45" x 7.20" x 2.80" (265mm x 183mm x 71 mm) active cooling 9.51 lbs. (4.31 kg) active cooling **plus** 1.43 lbs. (0.65 kg) for AC power module and AC power cord

## POWER CONSUMPTION

< 33 watts (when sweeping or streaming I/Q) sourced from the AC wall adapter which is included or from an external supply of 9VDC to 16VDC when using the Option-12 LEMO Pigtail.

## CONNECTIVITY

- 10GbE SFP+ port is used to send commands to and stream calibrated IQ data from the SM435C. The USB port is used for firmware upgrades.

## GPIO PORT

- Used for antenna switching and in/out triggering.